

"Marked up" copy
of originally filed
application
(Specification
only)

Modulator and Demodulator (MODEM)

BACKGROUND OF THE INVENTION

The present invention [related] relates to a MODEM for use with Data Terminal Equipment (DTE) such as a computer or a facsimile apparatus for data communication via a telephone line, [between Data Terminal Equipment (DTE) such as a computer and a facsimile apparatus, more particularly] Specifically, the invention relates to a MODEM which selects [selecting] an appropriate modulating method from a plurality of modulating methods.

Description of the prior art:

Several kinds of [modulating] modulation methods are available in MODEMs. For example, [such as] frequency modulation, four-phase differential phase shift modulation, quadrature amplitude modulation, and phase amplitude modulation are available. Selection of these methods [depends] may depend, for example, on [a] the speed of communication [speed]. Recently, many [of] MODEMs, for example a MODEM incorporated in a facsimile apparatus, switch [a] the modulation/demodulation mode as well as communication speed[s] depending on the protocol. It is [crucially important] desirable to synchronize [a] the timing of a mode switch between a transmitter and a receiver. [In a conventional manner] Conventionally, DTE, [a] the host apparatus of a MODEM, selects an [operation] operational mode[, and t] The MODEM follows an instruction from the DTE to switch to the appropriate operational [operation] mode.



The DTE is connected [with] to the MODEM via a BUS[, and] The CPU [of] contained within the DTE [knows] distinguishes between transmitted/received data by reading/writing [and] to the transmitting-data-register and receiving-data-register which are both [are] housed [by] in the MODEM. [Also] In addition, the CPU
5 recognizes the present [operation] operational mode of the MODEM by reading the status[-displaying]-register, and switches [an] the operational [operation] mode of the MODEM by writing a mode number into the mode register. The modulating and demodulating portion [in] of the MODEM follows an instruction from the mode register, and reports the status of each operation to the DTE via the status[-display]-
10 register.

Before the ITU (International Telecommunication Union) announced the V.34 Standard based on the ITU-T Recommendation, [all the] many MODEMs used in [the] facsimile[s] machines were of the half-duplex type, and [no] timing was not available for transmitting a waveform simultaneously from [both sides of] the
15 transmitter and receiver. Therefore, [Only] either the transmitter or the receiver [one of the sides thus] transmitted a waveform. [Therefore, a] The sequence of signal-transmission[transmitting] was determined by a protocol such as the T.30 Standard.

An operation according to the T.30 Standard is explained below [here]:

[A] If the previous mode is [a] the receive [receiving] mode, and the content of
20 the received data is [judged to switch] determined to require the next mode [into] to be the transmitting mode [In this case], the DTE [judges] decodes the received data and instructs the MODEM to switch the mode[,; however,] [s] Software processing in the DTE [takes] requires time, however, [in anyway] and produces a signal gap between the end of the receiving signal and the start of the subsequent transmission
25 [transmitting signal]. [When employing a] In half duplex communication[, whatever] the signal gap length [may be, it] will not [be a] cause [of] a disruption in [stopping the] communication.

On the other hand, when the communication is [operated] based on the full duplex mode of the V.34 Standard, [the full duplex mode] signals are transmitted simultaneously from both sides [is employed only in] by communicating through a control[ling] channel, whereby signals are transmitted simultaneously from both sides]. Accordingly, when the previous mode [is] was the [ended in] full-duplex mode of the control[ling] channel, and [suppose] the next mode is [a]to be the receiving mode of a main channel₁[. Then]the DTE [is supposed to judge] determines the [data of] control[ling] channel data and [give an instruction of] gives a mode switching command to the MODEM. A problem occurs in the above case: The timing of the mode switch depends on an instruction from the DTE [side]. If processing the transmitted/received data by the DTE [would] takes time [on the DTE side], the MODEM cannot receive the main channel, [for the] because of a delay in switching from [the] receiving of control channel data of the previous mode to [the] receiving of main channel data of the [next] following mode [delays]. When a high speed MODEM [of a higher speed] is employed, processing data volume [per hour] increases, whereby [this] these [kind] types of problems frequently occur [more often].

When [the] a V.34 Standard half-duplex MODEM [of V.34 Standard] is [employed] used, the main channel of one-way communication and the control[ling] channel of two way simultaneous communication are alternately switched [over alternately]. In this case, if a signal gap [spans over] is greater than a specific period (0.1 seconds), an echo-suppressor is recovered, whereby the control[ling] channel cannot [be through] complete the two-way simultaneous communication, and the communication is [thus] unable to recover. In order to prevent this problem, the V.34 Standard specifies the signal gap to be within $70\text{ ms} \pm 5\text{ ms}$.

Therefore, a mechanism which shortens the processing time is required in an interface between the MODEM and the DTE. However, if the processing time can be shortened at the DTE side and switch timing can be [spanned less] accomplished in a shorter period in proportion to the signal gap length, monitoring the signal gap length desirably requires [around] approximately $\pm 5\text{ ms}$ accuracy. At the DTE side, [a] software for monitoring the MODEM status thus desirably requires [a] top priority, whereby the system design of the DTE [encounters the difficulty]becomes difficult.

SUMMARY OF THE INVENTION

The present invention overcomes the problems [proper to] of the conventional methods, and shortens the processing time of the interface between the DTE and MODEM as well as [switches a] switching operational modes independent[ly] of the DTE's software. [the MODEM according to the present invention has these two novelties.]

According to the present invention, an object program [of] containing the control procedure is [basically] stored in a memory means. Corresponding to the object program execution, an operational mode is switched automatically in accordance with [the] each procedure specified in advance[.]. [t]The procedure corresponding to the present operational mode being switched from the previous mode is automatically executed. In other words, the MODEM monitors the mode-switch-control [for itself] and executes [the] mode switching [by itself] independent[ly] of the host apparatus[,] DTE.

The basic structure of the present invention realizes this feature[:]. Because [since] the MODEM switches operational modes by itself, the DTE transfer efficiency [to DTE] is increased and a given timing is guaranteed, whereby data communications which desirably requires [a] delicate timing can be satisfied [through], [a] trouble-free communication is secured, and total communication efficiency is increased.

The present invention has various embodiments for this basic structure. First, data storage areas which temporarily store the data transmitted to/from the host apparatus are provided [to] in each operational mode. Accordingly, when the MODEM switches [the] modes [by itself], received data is written into [difference] different areas in response to each mode. If a response speed cannot [follow] match the MODEM's communication speed [even in a moment], [a] the received data of the next mode is stored in another area of the memory means[.]. Therefore, the received data of the next mode [thus] will not overwrite the received data [counterpart] of the previous frame.

In another embodiment, a data storage area comprises a pair of [two] areas [in pairs] corresponding to each operation. [,] [o] One area is a command storage area for storing commands from the data terminal equipment (DTE). [, and another] The second area is a data storage area for storing data from the DTE. When [a transmitted] data in a storage area is processed, [a] the command written by the host apparatus into the corresponding command storage area is checked, and an operation follows the command.

In a further [Further in another] embodiment, the data storage areas of each operational mode [has plural] have several banks. [, and] The data from the DTE is stored in each bank in [the] a unit [of] called a frame. An error-check is conducted on the stored data from the DTE. [,] If a data error is detected, [and] a "data error" is written into a status register, and [then] the received data which includes the data error[s] is canceled. In this embodiment, the data-error is [thus] not written in the corresponding bank, and [a] the memory capacity is utilized with [less waste] greater efficiency. Since the result of the error-check, i.e. data-error, is still maintained, [a] notice can be given to the DTE that a data-error has occurred-[is produced].

[Still further in] In another embodiment, [a] the transition time between [an] the end of a procedure and [a] the start of the next procedure is monitored and a specified operational mode is [to be] automatically started when the transition time exceeds a prescribed period. In this embodiment, the response-delay to the next mode is [thus] prevented[, where a procedure requires ± 5 ms accuracy for monitoring the signal gap length.

In [another] a different embodiment, a received data frame in the MODEM is [deframed] disassembled and analyzed to [judge] determine whether the data frame is an[RCP (return to control for partial page)] (RCP) frame [or not]. If the data frame is [judged the] an RCP frame, the operational mode is automatically switched from the main-channel-receiving-mode to the control[ling] channel mode, [whereby] thereby preventing [to] the missing of a control[ling]-channel-signal arriving within 75 ms after [ending] completing the main channel.

In a separate embodiment, the MODEM analyzes the received data. If the analysis [tells] determines that there is an end signal [of] in the control[ling] channel of a [special] pattern which [could] does not occur in a data transmission, the MODEM automatically switches [automatically] the operational mode from the control[ling] channel mode to the main-channel-receiving mode, [whereby] thereby preventing [to] the missing of a main channel signal arriving within 75 ms after [ending] completing the control[ling] channel.

Further, in another separate embodiment, the MODEM calculates an error quantity, and specifies the acceptable maximum error quantity. When [an] the error quantity exceeds this acceptable maximum error quantity, a retraining signal is sent to the communication line. The acceptable maximum error quantity may be [instructed] controlled by the DTE. Therefore, in this embodiment, when the quality of received data is [even] lower[ed] during data transmission, the load on the DTE [can be] is reduced and also [a] the quality level can quickly be recovered, [quickly] whereby the entire [a total] communication can end quickly.

[Still] Finally, in a separate embodiment[,], a timer is installed[,]. The timer [which] starts counting a prescribed time simultaneously when the MODEM transmits a specified signal to the communication line. When a response signal to the specified signal [during the prescribed time] is detected before the timer reaches the specified time, the timer is reset. [If the response signal is not detected from the line during the specified time] Otherwise, the DTE is [given a notice] informed of an abnormal transmission. [Therefore, in] In a normal operation where the response signal is detected from the line, the DTE [needs not know about] does not respond to the detection of the response signal, [whereby] thereby the DTE processing is never [interfered] interrupted. Therefore, [T] the load upon the DTE [thus can be] is reduced when [comparing] compared to the situation where the DTE is required to handle transmission line control [with when every monitor result is noticed to the DTE].

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram depicting a MODEM according to an exemplary embodiment of the present invention.

Fig 2 depicts a memory structure of a dual port RAM[in] of Fig 1.

Fig. 3 depicts a memory structure of a channel area [required] used to access a channel block of an exemplary embodiment of the present invention.

Fig. 4 details a bit map in the channel command illustrated in Fig. 3.

Fig. 5 details a bit map in the channel status illustrated in Fig. 4.

Fig. 6 depicts a relation between command areas, status areas and banks on the dual port RAM.

Fig. 7 depicts a memory structure detailing a bit map in the command area of the present invention.

Fig. 8 depicts a memory structure detailing a bit map in the status area in accordance with an exemplary embodiment of the present invention.

Fig. 9 depicts a memory structure showing a transmission interrupt in accordance with an exemplary embodiment of the present invention.

Fig. 10 depicts a memory structure showing a receiving interrupt in accordance with an exemplary embodiment of the present invention.

Fig. 11 depicts a situation of an error-frame being detected when a frame of received data[’s frame] is checked.

Fig. 12(a) depicts a conventional memory [still] storing an error-frame after error detection [being judged so].

Fig. 12(b) depicts a memory in accordance with an exemplary embodiment of [this] the present invention, which cancels an error-frame after error detection [when being judged so].

Fig. 13 depicts when an abort is detected in received data.

Fig. 14(a) depicts a conventional memory [still] storing an error-frame after error detection [being judged so].

Fig. 14(b) depicts a memory in accordance with an exemplary embodiment of [this] the present invention, which cancels an error frame after error detection [when being judge so].

Fig. 15 is a control flow chart depicting [an embodiment] of a mode switch [according to] in accordance with an exemplary embodiment of [this] the present invention.

Fig. 16 is a receiving side's flow chart depicting a facsimile sequence using a half duplex mode of the V.34 Standard according to in accordance with an exemplary embodiment of [this] the present invention.

Fig. 17 depicts a mode switch by RCP detection in accordance with an exemplary embodiment of [this] the present invention.

Fig. 18 depicts a sample of timing used in facsimile/data communication in the V.34 mode [according to this] in accordance with an exemplary embodiment of the present invention.

Fig. 19 depicts a circuit of a MODEM used in [an embodiment] accordance with an exemplary embodiment of [this] the present invention.

Fig. 20 is an [inner] internal block diagram of the EQM calculator as shown [showed] in Fig. 19. (EQM: eye quality monitor)

Fig. 21 is a flow chart to be executed by the controller as shown [showed] in Fig. 19 while in the data receiving mode.

Fig. 22 is a sequence diagram outlining a procedure of the V.34 half duplex communication mode used in [this] accordance with an exemplary embodiment of the present invention.

[PREFERRED EMBODIMENTS] DETAILED DESCRIPTION

Fig. 1 is a block diagram outlining a MODEM used in [this] accordance with an exemplary embodiment of the present invention. A MODEM 11 modulates and demodulates data. A facsimile controller 12 functions as a host DTE and processes data expansion and data recording. The MODEM 11 comprises a line controller 111, an analog front end processor [FEP] 112 (FEP[: front end processor]), a digital signal processor [DSP] 113 (DSP[: digital signal processor]) which digitally processes modulation and demodulation etc., a dual port random access memory [RAM] 114 (RAM) having two READ/WRITE access ports, and an interrupt controller 115.

The facsimile controller 12 comprises an image reader/recorder 123, an image data compressor/expander 122, a console 121 including a control panel, a working RAM 124 which temporarily stores image data, and a central processing unit [CPU] 125 [(central processing unit)](CPU) which controls operation of the entire apparatus.

5 A first access port of the dual port RAM 114 is connected [disconnected] to a BUS B1 in the MODEM 11, and a second access port is connected to a BUS B2 in the facsimile controller 12, so that READ/WRITE from the MODEM 11 and facsimile controller 12 can [be practiced] occur simultaneously.

10 [The present] In an exemplary embodiment of the present invention [employs the] a dual port RAM 114, [to be] is disposed between the DTE and MODEM, in order to increase [data-transmit-efficiency] data transmission efficiency [of the interface] between the DTE and MODEM as well as [reduces] reducing the time-load on the DTE software, [at the DTE side:] The dual port RAM 114 can transmit[s] data in a [unit of] data-frame unit. [which] The data-frame unit is an error detecting unit.
15 [A] The buffer area of the frame unit is not limited to one frame but extends to a block area linking [plural] several frames (hereinafter called as a channel block.)

Fig. 2 depicts a memory structure of the dual port RAM 114 shown in Fig. 1. A communication buffer is independently provided [to] for each mode, such as a channel block A [to] for the main channel, a channel block B [to] for the transmitter control[ling] channel, a channel block C [to] for the [to the] receiver control[ling] channel. Each communication buffer has [plural] banks 0 - 3. The channel blocks A, B, and C have channel area pointers (CH area pointer) and channel areas (CH area). The CH area pointers have information for accessing the CH area.

25 Fig. 3 depicts a memory structure required for accessing the channel blocks. A channel command is an area for storing a command, [which] The command switches a corresponding channel to the transmit [transmitting] mode or the receive [receiving] mode. A channel status is an area [to] for displaying the information about an error in transmitting/receiving [of] the corresponding channel.

30 Fig. 4 details an example of a bit map in the channel command shown in Fig.

3.

Fig. 5 details an example of a bit map in the channel status shown in Fig. 3.

The MODEM 11, [so] structured as above, is explained here when the V.34 half duplex standard is used in for [a] communication.[:]

[An] This embodiment [here] shows how to control data received [data] from the facsimile controller 12 independent[ly in each] of the operational mode.

5 When communicating [by] using the V.34 half duplex standard a [channel of] communication channel comprises a main channel and a control[ing] channel. [t]The main channel is used for image information in the facsimile communication. [,and t] The control[ing] channel is used for the communication of Phase B control information recommended in the T.30 Standard of the ITU-T. The main channel uses
10 [the] channel block A. [, transmitting of the controlling channel uses the] [c]Channel block B is used for transmitting the control channel, and [receiving of the controlling channel uses the] channel block C is used for receiving the control channel.

15 First, [a] the [transmitting] transmission-process of the control[ing] channel is described.[:] In phase B of the T.30 Standard, the MODEM 11 sets the channel mode (bit 7) of channel block B to a [at] "[bit] 1" in order to transmit the control[ing] channel. Data is written into the bank 0 of channel block B. The MODEM 11 recognizes the ["bit 1" of] Data Full/Empty display bit is a "1", confirms the [ending] completion of WRITE, reads the data from Bank 0, processes signals including modulation, and transmits data to the communication line. After transmitting data
20 [out of] from Bank 0, the MODEM 11 changes the [display bit of] Data Full/Empty display bit of Status 0 to "0".

When the [display bit of] Data Full/Empty display bit of Status 1 (which corresponds to Bank 1) is "0", the facsimile controller 12[, on the other hand,] writes the next data-frame into Bank 1 while the MODEM 11 transmits the [data of] Bank 0 data. After completing WRITE, the [display bit of] Data Full/Empty display bit of Status 1 is changed to "1". The MODEM 11 checks Status 1 after completing the transmission of Bank 0[, and w]When the [display bit of] Data Full/Empty display bit is "1" (in other words, the next data-frame was already written[-in already]), the [data of] Bank 1 data is transmitted the same way as the Bank 0 data was transmitted. [In the same manner]Similarly, Banks 2, 3, and 0 [in this sequence] are transmitted in this sequence in the [unit of] data-frame unit. Although the transmit[ting] command of the control[ling] channel is [in] being executed [execution], when the [display bits of] Data Full/Empty display bits of the Bank status in all Banks are [at] "0" and there is no data-frame [to be transmitted is] available for transmission, the MODEM changes the transmitting-error-display-bit of channel status B [into] to "1" and [gives a notice] information to the facsimile controller 12 of [an transmitting] a transmission error [of] in channel block B [to the facsimile controller 12].

[Second]Next, the receiving process of the control[ling] channel is described.[:] The MODEM 11 sets [a] the channel mode of channel command C [at] to "0" in order to receive the control[ling] channel[, and t]The MODEM 11 receives [as well as] and demodulates data, confirms that the [display bit of d]Data Full/Empty display bit of Status 0 (which corresponds to Bank 0 of channel block C) is "0", and writes one data frame into Bank 0. After the writing is completed [completing the write-in], the [display bit of] Data Full/Empty display bit of Status 0 is changed to "1" (Completing WRITE = READ Ready.) The facsimile controller 12 confirms that the [display bit of] Data Full/Empty display bit of Status 0 is "1", [then] and reads data [out of] from Bank 0. When the [display bit of] Data Full/Empty display bit of Bank 1 is "0", the MODEM 11 writes the next received data-frame [of receiving] into Bank 1 while the data of Bank 0 is being read by the facsimile controller 12. [In the same manner,] Bank 2, 3, and 0, in this sequence, are received and processed in [the unit of] data-frame units.

Although the receiving command of the control[ling] channel is [in execution] being executed, when the [display bits of] Data Full/Empty display bits of the Bank status [is] for all Banks are [at] "1" and [no] received data-frames cannot be written into the vacant banks of C channel block, the MODEM 11 changes the receiving error display bit of channel status C [into] to "1", and [gives a notice] informs facsimile controller 12 of a [receiving] receive error of channel block C [to the facsimile controller 12].

As described above, transmitting/receiving of the control[ling] channel is processed by using channel blocks B and C. Therefore, even if the receiving/[T]transmitting of the control[ling] channel is operated in a full-duplex-simultaneous-mode under the V.34 half duplex Standard, the MODEM and facsimile controller do not require complicated processes, but can deliver the transmitted/received data of the control[ling] channel [safely]securely and efficiently. The transmitting/receiving of the main channel [works same as]is identical to that of the control[ling] channel. Namely, setting [a]the channel-set-mode-bit of the channel command in channel block A [at]to "1" [can] switches to the transmit[ting]mode, and setting the channel-set-mode-bit of channel block A at "0" [can]switches to the receiving] receive mode. The transmitting/receiving operation of the main channel can [be thus practiced]therefore be implemented.

Further in the V.34 half duplex Standard, a mode switch such as [from]between the transmit[ting]/[receiving]receive operation of the control[ling]channel to the transmitting or [receiving]receive operation of the main channel, or vice versa can be executed.

Third, [a]the process of stopping the [transmitting] transmission of data is explained by referring to Figs. 6 - 10. Fig. 6 depicts the relationship between the command areas, status areas and banks on the dual port RAM 114. The command areas store instructions about operations sent from the DTE such as channel ending, etc. The status areas store the information about the communication buffer's status such as [display of] Data Full/Empty display, aborts, and errors. These areas are provided to each bank in order to strictly control the [ending]completion of the processes when each bank completes [to]a data [transmit]transmission [data]. Each bank stores data in the [unit of] data-frame unit which is the unit of error-detection.

Fig. 7 details a bit-map in the command area, and Fig 8 details a bit-map in the status area. These drawings show the command area and status area corresponding to Bank 0. [The same manner can be] This is similarly applied to Banks 1, 2 and 3. Fig. 9 depicts a memory structure showing [an interrupt in transmitting] a transmit interrupt. Fig. 10 is a memory structure showing a[an interrupt in] [receiving]receive interrupt.

Fourth, an operation of the above structure is explained.[:] [Regarding] With respect to the data [transmitting] transmission process, e.g. Channel A among [plural] several channels is used, the facsimile controller 12 confirms that the [display bit of] Data Full/Empty display bit of Status 0 is "0", and writes one transmit data-frame [transmit of transmitting] into Bank 0. When [completing] the write is completed, the facsimile controller 12 changes the ending-channel-instruction-bit to "0" (not end), and changes the [display bit of] Data Full/Empty display bit of Status 0 to "1" (WRITE end = READ enable).

When the MODEM 11 recognizes that the [ending-channel-instruction-bit of] Command 0 ending-channel instruction bit is "0" and the [display bit of] Data Full/Empty display bit of Status 0 is "1", the MODEM 11 reads data [out of] from bank 0 to process signals such as demodulation, and transmits data to line L. When [completing to] the [transmit]transmission of the data [out of]from Bank 0[,] is complete, the MODEM 11 changes the [display bit of data full/empty] Data-Full/Empty display bit of status 0 to "0" [, then] and simultaneously the interrupt controller 115 produces an interrupt [in] to the facsimile controller 12.

The facsimile controller 12 inspects [a]the transmit-interrupt status shown in Fig. 9, [thereby notices]and determines that the MODEM 11 completed [to read] the data [out of]read from Bank 0. When the [display bit of] Data Full/Empty display bit of Status 1 [corresponding to Bank 1] is "0", the facsimile controller 12[, on the other hand,] writes the next data-frame into Bank 1 while the MODEM 11 transmits the data [of]from Bank 0. After completing the WRITE, the ending-channel-instruction-bit of Command 1 is changed to "1". The MODEM 11 checks Status 1 after completing the transmission of Bank 0, and when the [display bit of] Data Full/Empty display bit is "1" (in other words, the next data-frame was already written-in [already]), the [data of] Bank 1 data is transmitted [as same as]in an identical manner as the Bank 0 data., and if] If there is no ending-channel-instruction, the MODEM 11 moves to the next bank. [In the same manner]Similarly, Bank 2, 3, and 0, in this sequence, are transmitted in the [unit of] data-frame unit. When ending a data-[transmitting] transmission (channel A), a data-frame is written into [e.g.] Bank 3 (for example), the [display bit of] Data Full/Empty display bit of the Bank 3 Status [3] is changed to "1", and simultaneously the ending-channel-instruction-bit of the Bank 3 Command [3] is changed to "1", thereby giving the MODEM 11 [is given] an ending notice. The MODEM 11 checks the Bank 3 Status [3] and the Bank 3 Command [3] at the same time, [whereby] recognizes that both the [display bit of] Data Full/Empty display bit [is "1"] as well as the ending-channel-instruction bit are "1", [then ends]thereby completing the data [transmitting] transmission process after transmitting the Bank 3 data.

Fifth, a data receiving process is explained here.[:] The MODEM 11 demodulates the received data, and recognizes the [display bit of] Data Full/Empty display bit of Status 0 is "0" [to]and writes one data-frame into Bank 0. When [completing]the WRITE is completed, the MODEM 11 changes the [display bit of] Data Full/Empty display bit of Status 0 to "1" (WRITE end - READ enable.) The interrupt controller 115 produces an interrupt [on]to the facsimile controller 12.

The facsimile controller 12 inspects [a]the receiving-interrupt-status, and recognizes that data has been written into Bank 0. When receiving one data-frame, the MODEM 11 checks whether an abort [occurs or not]has occurred, inspects a frame-check-sequence which is added to the frame-end, and [judges]determines whether an error exists [or not]. The [judgment]result is [displayed on]indicated in the receiving-interrupt-status. After confirming [no]that an abort [exists in]did not occur, by inspecting the receiving-interrupt-status, and [also no]an error is not occurring in the data-frame, the facsimile controller 12 reads the data [out of]from Bank 0. When the [display bit of] Data Full/Empty display bit of Bank 0 is "0", the MODEM 11 writes the next data-frame into Bank 1 while the [data of] Bank 0 data is read by the facsimile controller 12. After completing the WRITE, the data written into Bank 1 is read by the facsimile controller 12, [same]in the same way as the data in Bank 0 was read. In the same manner, Bank 2, 3 and 0, in this sequence, are processed for receiving [in] the [unit of] data-frame unit.

When an error occurs in a data-frame or [in] an abort is detected due to line interference [in]while receiving data, how to cancel [an]the error frame is explained by referring to Fig. 11 through Fig. 14[:]. Fig. 11 depicts [a]the status of an error frame [being] detected when the receiving data-frame is checked. Fig. 12(a) depicts a memory where an error-frame is still [conventionally] stored even when the frame has been [judged]determined to be an error-frame. Fig. 12(b) depicts a memory where an error-frame is canceled according to this invention.

Fig. 13 depicts [a] received data where an abort is detected. Fig. 14(a) depicts a memory where the abort frame is still [conventionally] stored even when the frame has been [judged]determined as having an abort. Fig. 14(b) depicts a memory where the abort frame is canceled according to this invention.

When an error is detected by an error-detecting-signal (frame-check-sequence-error), a frame n (error-frame) is written into Bank 1, and an interrupt is produced in the facsimile controller 12 by the interrupt controller 115. The facsimile controller 12 inspects the receiving-interrupt-status to find that the data has been written into Bank 1 [as well as]and that the frame-check-sequence-error also has been [produced also in]written into Bank 1. The facsimile controller 12 does not read the data, because the data in Bank 1 has an error, and waits for the next data-frame.

When receiving the next data-frame $n+1$, the MODEM 11 does not write [it] data frame $n+1$ into Bank 2. Rather, data frame $n+1$ is written [but writes it] into Bank 1 [again] as shown in Fig. 12(b). When the WRITE is complete[d], an interrupt is produced [on]to the facsimile controller 12 by the interrupt controller 115. When receiving the interrupt, the facsimile controller 12 inspects the receiving-interrupt-status to find that the next data-frame $n+1$ has been written into Bank 1, and [practices]completes a receiving process. When the abort occurs, the same procedures are taken as shown in Fig. 13 and Fig. 14(b).

A mode switch process, where the MODEM 11 executes the mode switch by itself, is explained here by referring to Fig. 15 through Fig. 17. Fig. 15 is a control flow chart depicting [an embodiment of this]the mode switch process according to an exemplary embodiment of the present [this] invention.

First, the facsimile controller 12 sets a comprehensive mode (S401) which can control a previous and a next mode[s] in sequence. Second, the MODEM 11 follows an instruction [of]for executing the comprehensive mode (S402) from the facsimile controller 12, and executes S401 to start processing the previous mode. The facsimile controller 12 then waits for a notice from the MODEM 11 that the previous mode [is]has ended (S403). When the previous mode [is]has ended, the MODEM 11 gives a notice of [ending]the completion of the previous mode to the facsimile controller 12, and the MODEM 11 sets a timer [by itself] and monitors [a transit]the time before the next mode [is started]starts. When receiving the notice [of ending]that the previous mode has ended, the facsimile controller 12 selects one mode from among several modes and instructs the MODEM 11 to execute it in the next mode (S404)[,]. The facsimile controller 12 then waits for a notice [of ending]that the next mode has ended from the MODEM 11 (S405). When the timer [is]times out, the MODEM 11 executes the selected mode and monitors the status before giving a notice of [ending]completion of the next mode to the facsimile controller 12. When receiving the notice of [ending]completion of the next mode, the facsimile controller 12 ends the sequence of the comprehensive mode.

As explained above, according to this invention, the MODEM 11 automatically executes the mode switch process by simply following the [instruction of] mode setting instructions from the facsimile controller 12[, and t]. There is no need to wait for a mode-switch-instruction or process-start-instruction from the facsimile controller 12. [This] Therefore, according to an exemplary embodiment of the present invention [thus prevents] a response delay to the next mode is prevented even [in the procedure] where ± 5 ms accuracy is required for monitoring the signal-gap-length.

In other words, if the MODEM stores a communication sequence beforehand and the comprehensive mode is set to identify which mode is to be executed, the MODEM can execute the process by itself by controlling a status transition.

[Also] In addition, according to an exemplary embodiment of the present [this] invention, the MODEM monitors the timing required until the next mode starts. [, thereby] Therefore a delay [of] in switching to the next mode can be avoided even [if the case requires] when ± 5 ms accuracy in monitoring the signal-gap-length is desired.

As shown in Fig. 15, an exemplary embodiment of the present [this] invention proves the following [merits] benefits: When the process of the previous mode ends at S403, the MODEM 11 controls a status-transition [by itself] and also the next mode is set at S404 by the instruction of selecting the next mode, [and] thereby [a] guaranteeing the timing for the mode-switch [is guaranteed to secure a safety] resulting in efficient communication. Further, the MODEM can monitor the timing instead of the facsimile controller 12, [whereby] thereby reducing the load [from] on the facsimile controller 12.

Various mode-switches by the MODEM are explained. Fig. 16 [depicts a meaning] shows that the MODEM 11 has several operational-modes and another operational mode having a sequence which controls the several operational-modes. Fig. 16 is a flow-chart of a facsimile sequence using the half-duplex V.34 Standard based on the ITU [advice]. Phase 1 (S431), Phase 2 (S432), Phase 3 (S433), the controlling channel (S434), and the main channel (S435) are the modes in the sequence. The MODEM 11 has the half-duplex mode of the V.34 Standard into which these modes are [collected] combined.

A MODEM mode is set [at] as the V.34 half-duplex mode before the operation is started. Phase 1 of Step S431 starts, where an adjustment is made so that the data based on the V.34 Standard can be transmitted/received. When Step S431 is complete[d], the MODEM 11 transfers to Phase 2 of Step S432 to [learn] determine the line's characteristics and [determines a] the symbol speed of the MODEM. At Step S433, the MODEM [comes into] is at Phase 3 where [an] equalizer-training (set a coefficient in order to [figure out] determine distortion components) to the MODEM 11 is provided. After Phase 3, the MODEM [comes into] is at Step S434, the control[ling] channel, where [a] the data speed is determined and terminal information of the T.30 Standard is exchanged.

When the control[ling] channel ends, the MODEM [comes into] is at Step S435, the main channel, where the image data of the facsimile is transferred. When the main channel ends, the MODEM [stays in] enters Step S436 to determine [which way to go] what to do next.[:] Based on [by] an instruction [of] from facsimile controller 12, the MODEM will either proceed to 1) Step S437, where the control[ling] channel [which] resets [a] the data-speed; or 2) to Step S438, where the control[ling] channel [which] does not reset [a] the data-speed. [For this, the facsimile] Facsimile controller 12 gives [an] this instruction to the MODEM 11 to determine [which way to go] the next step, [Step] S437 or S438, before [ending] completing the main channel in Step S435.

The MODEM 11 in Step S439, after [moving to] completing either Step S437 or Step S438, determines whether the operation is to end[s or not]. When the operation does not end, the MODEM returns to Step S435, and continues to receive the main channel data. [, and when the operation ends,] Otherwise, the MODEM ends the operation. [A] The non-signal period between Phase 1 and Phase 2 is 75 ± 5 msec, and other non-signal periods between any modes [last] is 70 ± 5 msec. If the facsimile controller 12 controls [them] the modes, the facsimile controller 12 [must bear a heavy load] has additional functions to perform. According to an exemplary embodiment of the present [this] invention, the MODEM controls [them] the modes in lieu of the facsimile controller 12 so that the load on the facsimile controller 12 [can be] is reduced.

The above description is for the MODEM 11 to switch the modes by itself (the main channel, transmitting the control[ling] channel, and receiving the control[ling] channel.) By referring to Fig. 17 and Fig. 18, [an explanation is referred to] it is explained that the MODEM 11 [by] itself detects the end of the mode shown in S403 and S405 in Fig. 15. Fig. 17 depicts MODEM mode switching by RCP detection.

This is an example [when] where a facsimile communication or data communication is executed in accordance with the V.34 Standard. Fig. 17 shows a [timing of] mode switching timing from the main channel upon [its] completion to the control[ling] channel mode. Since the facsimile/data communication based on the V.34 Standard is operated in an error coorection [ECM] mode [(error correction mode) whose premise is] (ECM) based on "error-retransmitting", it is certain that the main channel [is to] ends with an RCP frame which is an end signal of a partial page. If the MODEM can [judge] determine the RCP frame in the MODEM, and can switch [a] the mode to the control mode, the MODEM never misses the control[ling]-channel-signal arriving within 75 ms after the main channel ends. [Inside of] The RCP frame is structured by the High-level Data Link Control [HDLC-method-] framing method (HDLC), and the MODEM 11 [must have an] desirably has the ability to execute a deframing operation. After deframing, if the data is [judged] determined to be correct, it is easy to [judge] analyze the RCF BYTE.

Another embodiment of the present invention, [for] where the MODEM 11 [to switch a mode] switches modes by itself, is explained by referring to Fig. 18. Fig. 18 shows an example of timing in which a facsimile/data communication in accordance with the V.34 Standard is operated. In particular, it shows the timing with which the control[ling] channel mode, upon completion, is switched to the main channel receiving mode.

Regarding the end of the control[ling] signal, the channel ending signal is specified by a rule of protocol. In this case also, the [ending of] channel end is [judged] determined by the MODEM 11 [by] itself rather than by the facsimile controller 12, thereby switching the mode [into] to the main receiving mode. [To be more specific] Specifically, the channel ending signal is [other than nothing to receive "1"] a sequence of consecutive [in] "1s" of not less than 40 bits, which can be detected in the MODEM.

As explained above, the MODEM 11 analyzes the received data [by itself], and when the analysis [tells]indicates that the specified signal has been detected, the MODEM switches [a]the mode based on the result of the detection. [The]Therefore, the MODEM [thus] never misses [a]the switch timing [of switch] and can guarantee [an] error-free communications.

Fig. 19 through Fig. 21 depict an instruction process [that]whereby the MODEM 11 instructs [by itself] the facsimile controller 12 [in a]into the retraining mode. Fig. 19 is a circuit diagram of MODEM 11, which shows an exemplary embodiment of [this] the present invention. In Fig. 19, a DTE-interface 617 controls data-transmission such as transmitted/received data as well as other data including instructions of modes, operations, etc. between the DTE and the MODEM. [A t]Transmitted data 613a is sent from the DTE to the other party of the communication via the DTE-interface 617. [A r]Received data 616a is transmitted from the other party to the DTE via the DTE-interface 617. An EQM threshold-value-signal 620b is [determined as] a reference value for [judging]determining a retraining control of the MODEM by the DTE via the DTE-interface 617. An encoder 613 transduces the transmitted [date]data 613a into two-dimensional-signals 612R and 612I. A quadrature amplitude [QAM] modulator (QAM) 612 provides quadrature amplitude modulation to the two dimensional signals.

The QAM modulator 612 is controlled so that the following signals are output as a [modulating]modulated signal 612a in response to the status of [a] control signal 620c:

[In the case of]Where: 620c = 0, no signal

620c = 1, quadrature amplitude modulation signal of the two dimensional signals 612R and 612I

620c = 2, training signal

620c = 3, retraining signal

620c = 4, response signal of retraining

A hybrid circuit 611 separates the signals of the transmitting system from those of the receiving system. This hybrid circuit sends out the transmitted signal 612a to a telephone line 611a, and outputs a received signal 614a from the other party.

[A] QAM demodulator 614 has two functions, [one]namely 1) for providing [provides] quadrature amplitude modulation to the received signal 614a to output a two-dimensional-signal 614R and 614I, and 2) for outputting [the other outputs] a judgment of the received signal 614a [to]as a judging signal 620a. The QAM
 5 demodulator 614 outputs as follows in response to the status of received signal 614a:

When received signal 614a = no signal, 620a = 0

= data receiving signal, 620a = 1

= training signal, 620a = 2

= retraining signal, 620a = 3

= retraining signal, 620a = 4

A judging part 615 [judges]analyses the two dimensional signals 614R and 614I. The [judged]analyzed signals 614R and 614I are tapped off from the judging part 615

A decoder 616 [transduces]decodes the [judged two dimensional] signals 615R
 15 and 615I into [the] received data 616a. An error counter 618 subtracts output signals 615R of judging part 615 from the output signal 614R of QAM demodulator 614, and also subtracts the output signals 615I of the judging part 615 from the output signal 614I of the QAM demodulator 614, [then]and outputs a two-dimensional-error signal 618 and 618I. The eye quality monitor [EQM] calculator 619 (EQM) calculates [a]the
 20 power of the two-dimensional-error-signals 618R and 618I, and then outputs [its signal as] an EQM signal 619a representing [a]the quality of the received data. [A c]Controller 620 receives [an] inputs consisting of three signals, namely, the EQM signal 619a, the EQM threshold value 610b, which is a reference value for retraining, the identifying signal 620a, which identifies the received signal[, and]. Controller 620
 25 outputs [the]a control signal 620c to the QAM modulator 612.

Fig. 20 is a block diagram of [inside] the EQM calculator 619. Multipliers 621 and 622 square the two-dimensional-error-signals 618R and 618I, respectively. [An a]Adder 623 adds the signals squared by [the] multipliers 621 and 622 and [ouputs]outputs a power signal 623a of the two-dimensional-error. [An
 30 integrator]Integrator 624 smoothes the power signal 623a of two-dimensional-error, and outputs the EQM signal 619a representing the quality of receiving data.

Fig. 21 is a flow [chart] diagram which illustrates the steps which may [should] be executed in data-receiving-mode by the controller 620 shown in Fig. 19. Step S601 sets the MODEM [in] into a waiting status for the training signal to be detected, and sets the signal 620c to "0" [for] instructing QAM modulator 612 [to send no] not to send a signal. Step S602 judges whether the MODEM 11 detect[s] ed the training signal sent from the MODEM of the other party [of] to the communication [or not]. When S602 [judges] determines a "detected" state, the operation moves to S603, otherwise, the operation repeats [the] step S602. When [a] signal 620a changes to "2", the training signal [is judged to be] has been detected. In [the] step S603, the MODEM is set in training-signal-receiving-status. In step S604, the controller 620 [judges] determines whether the training-signal-receiving [ends or not] has ended. When the training-signal-receiving ends, the operation moves to S605, [and when not ends,] otherwise S604 is repeated. When the signal 620a changes from "2" to "1", the training-signal-receiving [is judged to end] has ended.

In step S605, the MODEM is set [in receiving status] to the receive mode, where [receiving] received data is transmitted to the DTE via the QAM demodulator 614, judging part 615, decoder 616 and DTE-interface 617. Step S606 judges whether the EQM signal 619a representing the quality of receiving data exceeds the EQM threshold value 620b or not. When the EQM signal 619a exceeds the threshold value 620b, the operation moves to step S609, and when the threshold value 620b exceeds the EQM signal 619a, the operation moves to step S607

Step S607 [judges] determines whether data-receiving [ends or not] is completed. When the data-receiving [ends] is completed, the operation moves to Step S608, [and when not ends,] otherwise the operation returns to Step S606. The criteria [of this judgment whether the data-receiving ends or not is] for this determination is: when signal 620a changes from "1" to "0", and when an "end" state is instructed by [th3e] the DTE via the DTE-interface 617.

Step S608 sets the MODEM [in]to a data-ending status, [and] stops the received data [to be transmitted]from further transmission to the DTE via the DTE-interface 617, and [then moves to]enters an idle mode. Step S609 sets the MODEM [in]to a retraining-signal-transmitting status, changes the signal S620c to "3",
5 transmits the retraining signal from the QAM modulator 612, and moves to Step S610. At this [moment]time, the operation temporarily stops the [receiving]received data from being transmitted to the DTE via the DTE-interface. Step S610 [judges]determines whether the MODEM 11 detect[s]ed a retraining response signal from the MODEM of the other party [of]to the communication [or not]. When a
10 "[detects]detected" state is entered, the operation repeats Step S601, [and when "not detects"]otherwise the operation repeats Step S610. [A]The criteria [of the judgment is this]for this determination is: when [the] signal 620a changes to "4", it is [judged]determined that the retraining signal is detected.

In the above embodiments, retraining is controlled by both the EQM threshold
15 value set by the DTE and the EQM value set by the MODEM 11. However, this invention is not limited to these embodiments, but has other structures for controlling the training. For example, a frame-error or bit-error is monitored in the MODEM, and the DTE sets a threshold value to the monitoring, thereby the training is controlled. According to the above embodiments, the DTE [instructs]controls the
20 EQM threshold value. However, the EQM threshold value may be held before-hand by the MODEM [before-hand instead].

Next, a process of monitoring the timing by the MODEM is explained. Fig. 22 is a sequence diagram outlining the procedure of the V.34 Standard half-duplex mode. First, a [timing]timer T1 works as follows: On the receiver side,
25 [when]concurrent with the [transmitting]transmission of the Answer tone (ANSam) signal [starts, at the same time,]is the decrementing of the time (e.g. 35 seconds) set in [the] timer T1 [starts]. If [the] timer T1 counts down to "0", the MODEM 11 gives [a notice of abnormal]an abnormal indication by producing an interrupt to the
DTE side. However, when a Call Menu (CM) signal from a caller is detected before
30 the timer T1 counts down to "0", the decrementing of [in the] timer T1 is stopped.

On the caller side, [at the same time when] concurrent with the receiving the ANSam signal, is the decrementing of time (e.g. 35 seconds) set in [the] timer T1 provided from the facsimile 12 [starts]. If [the] timer T1 counts down to "0", the MODEM produces an interrupt to the DTE side, thereby [give a notice of abnormal] giving an abnormal indication. [However] If, a JM signal from the receiver side is detected before the timer T1 counts down to "0", however, the decrementing [in the] of timer T1 is stopped.

It is possible to start the [decrements] decrementing on both sides, i.e. the caller side and receiver side, at the same time when the terminal is linked [up] to the telephone line.

Second, a timer T2 works as follows: On the receiver side, at the same time [when] as the [transmitting] transmission of the Non-Standard Facilities (NSF), Called Subscriber Identification (CSI) and Digital Identification Signal (DIS) signals ends, the decrementing of time (e.g. 6 seconds) set in the timer T2 provided from the DTE side starts. If the timer T2 counts down to "0", the MODEM produces an interrupt, thereby [gives a notice of abnormal] indicating an abnormal condition. However, before the timer T2 counts down to "0", if the signals [to be appeared] Transmitting Subscriber Identification (TSI) and Digital Command Signal (DCS) [signals could be] are detected from an address byte to control byte according to HDLC format, then the decrementing of timer T2 [is stopped] stops and timer T2 is returned to its original time, thereby avoiding an interrupt [of producing] indicating an abnormality [can be avoided]. As explained above, this invention only gives a notice that an abnormality [is produced] has occurred. When an operation is normal, the DTE need[s] not [to] be [noticed] informed of normal[ity] operation[, which does not bother the procedure]. Therefore, [the] in this method such [as a] notice is given only when an abnormality occurs, [can] thereby [reduce] reducing the load on the facsimile controller 12.

On the caller side, at the same time when [transmitting] transmission of the TSI and DCS signals ends, the decrementing of time (e.g. 6 seconds) set in the timer T2 provided from the DTE side starts. If the Timer T2 counts down to "0", the MODEM produces an interrupt to the DTE side, thereby [gives a notice of abnormal] indicating an abnormal condition. However, before the timer T2 counts down to "0", if [a signal to be appeared] the Confirm to Receive (CFR) signal [would be] is detected from the address to control bytes following the HDLC format, the decrementing of the timer T2 stops and timer T2 returns to its original time, thereby avoiding an interrupt [of abnormal can be avoided] indicating an abnormality.

The above exemplary embodiment handles the timer T2 put in just after Phase B [moving] moves from Phase A. Regarding the control signals including the Multipage (MPS) signal between pages, End of Procedure (EOP) and Message Confirmation (MCF) signals in Phase B passing through Phase C, the DTE side can monitor [the] timer 2 [with ease by] easily using the same method.